

Daker DK

UPS
SINGLE-PHASE
from 1000
to 10000 VA



THE **GLOBAL SPECIALIST**
IN ELECTRICAL AND DIGITAL BUILDING INFRASTRUCTURES



Daker DK CONVENTIONAL SINGLE PHASE UPS

On-Line double
conversion UPS that can
be used in both tower
and rack configurations

The main parameters of the system and the status of the UPS, including the battery charge level and faults, are displayed on the LCD screen.

Additional battery cabinets are available to increase the backup time of the UPS. A charger can be added in all battery cabinets for fast, safe charging.



Reversible screen

With the reversible screen, the Daker DK UPS can be used in both tower and 19» rack configuration.

Daker Dk

Conventional UPS - Single phase On-line double conversion VFI



The main parameters of the UPS, including the battery charge level and faults, are displayed on the LCD screen on the front panel. The integrated communication software not only controls the UPS and its switch-off if there is a malfunction, and enables the user to test the main functions remotely, communicate via SNMP/Internet/network adaptor and access the functions of the UPS via the Internet, but can also send the user an SMS if specific events occur. The internal extension connector enables a WEB/SNMP card or a relay interface to be installed which provides insulated contacts for applications on industrial control panels or remote alarm panels. If there is an electronic fault, overload, overheating or for scheduled maintenance operations, the automatic or manual (optional) bypass ensures continuity of the power supply for critical loads. A bypass switch is available for maintenance.

Pack	Cat. Nos.	CONVERTIBLE UPS WITH BATTERIES			
		NOMINAL POWER (VA)	ACTIVE POWER (W)	BACKUP TIME (min)	WEIGHT (kg)
	3 100 50	1000	800	10	16
	3 100 51	2000	1600	10	29.5
	3 100 52	3000	2400	8	30
	3 100 53	4500	4050	6	60
	3 100 54	6000	5400	4	60

Pack	Cat. Nos.	CONVERTIBLE UPS WITHOUT BATTERIES			
		NOMINAL POWER (VA)	ACTIVE POWER (W)	BACKUP TIME (min)	WEIGHT (kg)
	3 100 56	4500	4050	-	25
	3 100 57	6000	5400	-	25
	3 100 58	10000	9000	-	26

BATTERY CABINET (WITH BATTERIES)	
	DESCRIPTION
3 107 69	Battery cabinet for 3 100 50 (12 x 12 V, 7.2 Ah batteries)
3 107 70	Battery cabinet for 3 100 51 (12 x 12 V, 7.2 Ah batteries)
3 107 71	Battery cabinet for 3 100 52 (12 x 12 V, 9 Ah batteries)
3 107 72	Battery cabinet for 3 100 56 and 3 100 57 (20 x 12 V, 7.2 Ah batteries)
3 107 66	Battery cabinet for 3 100 58 (20 x 12 V, 9 Ah batteries)

BATTERY CABINET (EMPTY)	
	DESCRIPTION
3 107 50	Battery cabinet for 3 100 50 (for 12 x 12 V, 7.2 Ah batteries)
3 107 51	Battery cabinet for 3 100 51 (for 12 x 12 V, 7.2 Ah batteries)
3 107 52	Battery cabinet for 3 100 52 (for 12 x 12 V, 9 Ah batteries)
3 107 53	Battery cabinet for 3 100 56 and 3 100 57 (for 20 x 12 V, 7.2 Ah batteries)
3 107 54	Battery cabinet for 3 100 58 (for 20 x 12 V, 9 Ah batteries)

Pack	Cat. Nos.	MISCELLANEOUS ACCESSORIES	
			DESCRIPTION
	3 109 50		Additional 200 W charger (for Daker DK 1000-2000-3000)
	3 109 54		Additional 1000 W charger (for Daker DK 4500-6000-10000)
	3 109 52		Rack support bracket kit
	3 109 53		External manual bypass (for Daker DK 1000-2000-3000)
	3 109 69		Volt-free contact card

NOTE: The backup times, expressed in minutes, are measured under optimum operating conditions.

Daker Dk

Conventional UPS - Single phase On-line double conversion VFI

Cat. Nos.	3 100 50	3 100 51	3 100 52	3 100 53	3 100 56	3 100 54	3 100 57	3 100 58
General characteristics								
Nominal power (VA)	1000	2000	3000	4500		6000		10000
Active power (W)	800	1600	2400	4050		5400		9000
Technology	On-line double conversion VFI-SS-111							
Waveform	Sinusoidal							
Architecture	Convertible tower and 19" rack							
Input characteristics								
Input voltage	230 V							
Input frequency	50-60 Hz ± 5% autosensing							
Input voltage range	160 V - 288 V full load							
THD of input current	< 3%							
Input power factor	> 0.99							
Compatibility with gensets	Configurable for synchronism between the input and output frequencies, even for the highest frequency ranges, ± 14%							
Output characteristics								
Output voltage	230 V ± 1%							
Output frequency (nominal)	50/60 Hz (configurable via LCD panel) +/- 0.1%							
Peak factor	1:3							
THD of output voltage	< 3% with linear load							
Output voltage tolerance	± 1%							
Bypass	Automatic bypass and optional external manual bypass							
Batteries								
Backup time extension	Yes							
Number of batteries	3	6	6	20	-	20	-	-
Battery range type/voltage	12 V 7.2 Ah	12 V 7.2 Ah	12 V 9 Ah	12 V 5 Ah	-	12 V 5 Ah	-	-
Backup time (min)	10	10	8	6	-	4	-	-
Communication and management								
Screen and signalling	Four buttons and four LEDs for real-time control of the status and the main parameters of the UPS							
Communication ports	RS232 and USB serial ports			RS232 serial ports				
Remote control	Available							
Connector for network interface	SNMP							
Mechanical characteristics								
Dimensions (H x W x D) (mm)	440x88 (2U) x405	440x88 (2U) x650	440x88 (2U) x650	440x176 (4U) x680	440x88 (2U) x680	440x176 (4U) x680	440x88 (2U) x680	440x132 (3U) x680
Dimensions of battery cabinet H x W x D (mm)	440x176 (4U) x405	440x88 (2U) x650	440x88 (2U) x650	-	440x132 (3U) x680	-	440x132 (3U) x680	440x132 (3U) x680
Net weight (kg)	16	29.5	30	52	25*	52	25*	26*
Ambient conditions								
Operating temperature (°C)	0 ÷ 40°C							
Protection index	IP 21							
Relative humidity (%)	20 to 80%							
Noise at 1 m (dBA)	< 50							
Heat dissipation (BTU/h)	490	654	818	982		1310		1636
Certifications								
Reference product standards	EN 62040-1, EN 62040-2, EN 62040-3							

* Weight without batteries

NOTE: The backup times, expressed in minutes, are measured under optimum operating conditions.

Daker Dk

Long backup time table

Model	Power	Backup time	Dimensions and number of cabinets H x W x D (mm)	Cat. Nos.
Daker DK	1000 VA	10'	440 x 88 x 405	3 100 50
		1h 22'	440 x 88 x 405 + 440 x 176 x 405	3 100 50 + 3 107 69
		2h 44'	440 x 88 x 405 + 440 x 176 x 405 (x2)	3 100 50 + 3 107 69 (x2)
		4h 22'	440 x 88 x 405 + 440 x 176 x 405 (x3)	3 100 50 + 3 107 69 (x3)
		5h 52'	440 x 88 x 405 + 440 x 176 x 405 (x4)	3 100 50 + 3 107 69 (x4)
	2000 VA	10'	440 x 88 x 650	3 100 51
		39'	440 x 88 x 650 (x2)	3 100 51 + 3 107 70
		1h 22'	440 x 88 x 650 (x3)	3 100 51 + 3 107 70 (x2)
		1h 57'	440 x 88 x 650 (x4)	3 100 51 + 3 107 70 (x3)
		2h 44'	440 x 88 x 650 (x5)	3 100 51 + 3 107 70 (x4)
	3000 VA	8'	440 x 88 x 650	3 100 52
		34'	440 x 88 x 650 (x2)	3 100 52 + 3 107 71
		1h 6'	440 x 88 x 650 (x3)	3 100 52 + 3 107 71 (x2)
		1h 33'	440 x 88 x 650 (x4)	3 100 52 + 3 107 71 (x3)
		2h 3'	440 x 88 x 650 (x5)	3 100 52 + 3 107 71 (x4)
	4500 VA	10'	440 x 88 x 650 + 440 x 132 x 680	3 100 56 + 3 107 72
		31'	440 x 88 x 650 + 440 x 132 x 680 (x2)	3 100 56 + 3 107 72 (x2)
		56'	440 x 88 x 650 + 440 x 132 x 680 (x3)	3 100 56 + 3 107 72 (x3)
		1h 30'	440 x 88 x 650 + 440 x 132 x 680 (x4)	3 100 56 + 3 107 72 (x4)
	6000 VA	10'	440 x 88 x 650 + 440 x 132 x 680	3 100 57 + 3 107 72
		29'	440 x 88 x 650 + 440 x 132 x 680 (x2)	3 100 57 + 3 107 72 (x2)
		49'	440 x 88 x 650 + 440 x 132 x 680 (x3)	3 100 57 + 3 107 72 (x3)
		1h 11'	440 x 88 x 650 + 440 x 132 x 680 (x4)	3 100 57 + 3 107 72 (x4)
	10000 VA	7'	440 x 132 x 650 + 440 x 132 x 680	3 100 58 + 3 107 66
		18'	440 x 132 x 650 + 440 x 132 x 680 (x2)	3 100 58 + 3 107 66 (x2)
		29'	440 x 132 x 650 + 440 x 132 x 680 (x3)	3 100 58 + 3 107 66 (x3)
		42'	440 x 132 x 650 + 440 x 132 x 680 (x4)	3 100 58 + 3 107 66 (x4)
		56'	440 x 132 x 650 + 440 x 132 x 680 (x5)	3 100 58 + 3 107 66 (x5)

NOTE: The backup times, expressed in minutes, are measured under optimum operating conditions.

	1000 VA 2 cabinets W 2U + 4U	3000 VA 3 cabinets W 2U + 2U + 2U	6000 VA 2 cabinets W 2U + 3U	10000 VA 2 cabinets W 3U + 3U
TOWER version				

	1000 VA 2 cabinets H 6U (264 mm)	4500 VA 3 cabinets H 6U (264 mm)	6000 VA 2 cabinets 5U (320 mm)	10000 VA 2 cabinets H 6U (264 mm)
RACK version				



**World Headquarters and
International Department**
87045 Limoges Cedex - France
☎ : + 33 (0) 5 55 06 87 87
Fax : + 33 (0) 5 55 06 74 55